



















# Installation and Maintenance

## 1) Installation


### First Fix - Installation of housing and Finishing of Ceiling

<p><b>1</b> Drill 62mm hole</p> 	<p><b>2</b> Connect the neutral earth and live wires</p> 	<p><b>3</b> Insert housing in ceiling, twist to lock in place</p> 	<p><b>4</b> Insert plastering disk</p> 	<p><b>5</b> Skim ceiling (Housing lip should be visible after plastering)</p> 
<p><b>6</b> Skim ceiling flush with the housing edge</p> 	<p><b>7</b> Remove plastering disk</p> 	<p><b>8</b> Wipe excess plaster off the lip of the housing with damp cloth</p> 	<p><b>9</b> Insert painting card</p> 	<p><b>10</b> Paint the ceiling</p> 
<p><b>11</b> Remove painting card</p> 	<p>Lip of housing flush with ceiling</p> 	<p>Housing buried in plaster</p> 	<p>Retrofit hole-saw is available if you are not planning to plastering</p> 	

### Second Fix - Insert Luminaire and Light Source

<p><b>1</b> Pull supply connector out of the housing</p> 	<p><b>2</b> Plug luminaire connector into the supply connector</p> 	<p><b>3</b> Insert luminaire into the housing</p> 	<p><b>4</b> Put front plate on (Do not paint on ceiling)</p> 
--	--	---	--






### Painting Front Plates

<p><b>1</b> Place paintable front plate on a flat surface</p> 	<p><b>2</b> Apply paint with a small roller</p> 	<p><b>3</b> Once dried, remove sticker (IP65) and insert front plate into the fittings</p> 
---	---	--






**NB: Do not paint front plate while in the ceiling**

## 2) Maintenance

### Replacement of Lamp

<p><b>1</b> Remove luminaire insert from housing</p> 	<p><b>2</b> Unplug connector</p> 	<p><b>3</b> Remove and replace lamp</p> 	<p><b>4</b> Fit spring clip and lampholder</p> 	<p><b>5</b> Plug-in connector and insert into the ceiling</p> 
--	--	---	--	---

### Re-decorating

<p><b>1</b> Remove luminaire insert from the ceiling and unplug connector</p> 	<p><b>2</b> Insert painting card</p> 	<p><b>3</b> Paint the ceiling</p> 	<p><b>4</b> Remove painting card</p> 	<p><b>5</b> Insert luminaire into the housing</p> 
---	--	---	--	---